

Model No.	Rated Capacity	DC Voltage	No. of Battery	Battery Size	Backup Time (Hour)
PSI-500 WM-PSI-500 PSD-500 PSE-500	300W	12VDC	1	12V/ 50AH	1.24
				12V/ 75AH	1.85
				12V/ 100AH	2.47
				12V/ 150AH	3.71
				12V/ 200AH	4.95
PSI-800 WM-PSI-800 PSD-800 PSE-800	480W	12VDC	1	12V/ 50AH	0.77
				12V/ 75AH	1.16
				12V/ 100AH	1.55
				12V/ 150AH	2.32
				12V/ 200AH	3.09
PSI-1000 WM-PSI-1000 PSD-1000 PSE-1000	600W	24VDC	2	12V/ 50AH	1.24
				12V/ 75AH	1.85
				12V/ 100AH	2.47
				12V/ 150AH	3.70
				12V/ 200AH	4.94
PSI-1500 WM-PSI-1500 PSD-1500 PSE-1500	900W	24VDC	2	12V/ 50AH	0.82
				12V/ 75AH	1.24
				12V/ 100AH	1.65
				12V/ 150AH	2.47
				12V/ 200AH	3.30
PSI-2000 WM-PSI-2000 PSD-2000 PSE-2000	1200W	24VDC	2	12V/ 50AH	0.62
				12V/ 75AH	0.93
				12V/ 100AH	1.24
				12V/ 150AH	1.85
				12V/ 200AH	2.47